

Type: **NZM2/3-XUHIV380-440AC**

Article No.: **259594**


Sales text **Undervoltage release with 2 VHI**



For interlocking and load-shedding circuits, as well as for early-make of the undervoltage release in main-switch applications.

Ordering information

For use with			NZM2(-4), N(S)2(-4) NZM3(-4), N(S)3(-4)
Rated control voltage	U_s	V	380 V – 440 V 50/60 Hz



Notes concerning the product group

When the undervoltage release is de-energized, accidental contact with the main contacts of the switch during attempts to switch on is safely prevented.

Early-make of the auxiliary contacts with on and off switching (manual operation): approx. 20 ms.

Cannot be used in conjunction with NZM...-XR... remote operator.

Undervoltage releases cannot be installed simultaneously with NZM...-XHIV... early-make auxiliary contact or NZM...-XA... shunt release.

Undervoltage release

Rated control voltage			
AC	U_s	V AC	24...600
DC	U_s	V DC	12...250
Operating range			
Drop-out voltage		$\times U_s$	0,35 – 0,7
Pick-up voltage		$\times U_s$	0,85 – 1,1

Moeller GmbH, Hein-Moeller-Str. 7-11, D-53115 Bonn
E-Mail: catalog@moeller.net, Internet: www.moeller.net, <http://catalog.moeller.net>
HPL-C2007G V2.1 © 2007 by Moeller GmbH